

MODEL: **WC-P7750H**



APPLICATIONS



POWERED by **HONDA**



Open Frame AVR Generator
with Honda Engine

- Work sites to power small to medium tools and lights
- Home back-up solution for essential appliances
- Outdoor events for lights, sound systems etc
- Mobile businesses or market stalls for powering small appliances

Scan for more info



SPECIFICATIONS



AVR



2-WIRE
START



FUEL
EFFICIENT

PETROL GENERATOR: WC-P7750H	
Product Code:	811992
Generator Rating:	7.75kVA
Max AC Output:	6,000W
Rated AC Output:	5,500W
Rated Voltage:	240V AC
Type:	Open Frame AVR
Frequency:	50Hz
Connections:	2 x 15A IP66 1 x USB A (18W) 1 x USB C (15W)
ENGINE: Honda GX390	
Type:	Single cylinder, 4 stroke, OHV air-cooled petrol
Displacement:	390CC
Speed:	3600rpm
Low Oil/Petrol Warning:	Fitted
Ignition System:	DCDI with variable timing
Starting Type:	Recoil / Electronic / 2-Wire
Fuel Tank Capacity:	6L
Fuel Consumption	1.37 L/hr @ ¼ load
DIMENSIONS & PERFORMANCE	
Product Dimensions:	550 x 700 x 660mm
Dry Weight:	80kg
Operating Time at 25% Load:	4.4hr
Noise Level @ 7m:	89 dBA
Warranty:	3 Years Engine 2 Years Alternator & Frame